

BMZ Hyperion Compatibility Overview

Firmware Rev.: 4.21.R

released CW06 2024

Housing Article No.	Module		Compatibility					
	Article No.	Type	SMA SBS ⁽¹⁾	SMA STP SE ⁽²⁾	Kostal ⁽³⁾	GoodWe ⁽⁴⁾	SOFARSOLAR ⁽⁶⁾	Solis ⁽⁷⁾
41871	37832-02	Helios 1.5	3.7 / 5.0 / 6.0	./.	./.	./.	./.	./.
611280	37832-02	Helios 1.5	3.7 / 5.0 / 6.0	./.	./.	./.	./.	./.
615424	37832-02 ⁽⁵⁾ 612033, 626896 ⁽⁵⁾	Helios 1.5 Helios VE	3.7 / 5.0 / 6.0	./.	./.	./.	./.	./.
610853	612033, 626896	Helios VE	./.	./.	PLENTICORE plus/BI	./.	./.	./.
609678	612033, 626896	Helios VE	./.	./.	PLENTICORE plus/BI	./.	./.	./.
616038	612033, 626896	Helios VE	3.7 / 5.0 / 6.0	5.0 / 6.0 / 8.0 / 10.0	PLENTICORE plus/BI	ET PLUS+ Series	HYD/ME TL-3PH Series ⁽⁶⁾	S6-EH3P(3-10)K-H-EU ⁽⁷⁾

⁽¹⁾ Sunny Boy Storage Firmware version 0.03.15.R or newer - min. 3 modules

⁽²⁾ Sunny Tripower SE Firmware version 3.02.20.R or newer - min. 4 modules

⁽³⁾ PLENTICORE plus inverters requires an activation code from Kostal for using a Hyperion - min. 3 modules

⁽⁴⁾ ET PLUS+ Series (5-10 kW) with inverter ARM firmware version: V20 or higher version - min. 4 modules

⁽⁵⁾ In one Hyperion either only 37832-02 (Helios 1.5) or only 612033 (Helios VE) should be used

⁽⁶⁾ HYD 5K...20KTL-3PH and ME 5K...20KTL-3PH series with firmware V110022 or higher version - min. 4 modules

⁽⁷⁾ S6-EH3P(3-10)K-H-EU with inverter firmware V04-13 or higher version - min. 3 modules